



306ci/356ci/406ci Color Profile Release Notes

Subject:	Color Profile
Model	306ci/356ci/406ci
Updated Machines Serial Number:	N/N

Introduction:

Kyocera provides the option of registering two different Color Profiles on the MFP if the default Kyocera color reproduction does not meet your Customers needs.

Seven different Color Profiles are available for the 306ci/356ci/406ci. They are preloaded on the Standard Hard Drive for the 356ci/406ci. The Kyocera Color profile is the default for Copy/Print as Color Table 1 as referenced in U485.

Custom Color Profiles are not preloaded on the 306ci. Only one Color profile can be added to meet your customer's custom color reproduction requirements. A Hard Drive is not required, as the profile is loaded into memory.

The 356ci/406ci supports two color tables for the copying function and two for the printing function. The Copy Profile can be different then the Print Profile.

To select a copy function color table after entering maintenance mode U485, Select Color Table 1 (Copy) or Color Table 2 (Copy). Then select the desired profile. Remember only one color file can be selected for each table. Then, press the Start key to select this color profile. Press the Stop key to return to the color tables screen. Use the same procedure to set up the color tables for printing. Color table 1 prn is the default **Kyocera** color **Profile** for printing and can be overwritten if necessary. Color Table 2 prn can be selected by the user from the KX print driver. After all color tables have been specified press the Stop key again to exit maintenance mode U485, then exit the maintenance mode.

Color Profiles can be uninstalled by selecting the Print or Copy Uninstall buttons from MM U485 for the 356ci/406ci only.


Remember, you may have to experiment with the different color profiles until you find the right color reproduction to meet your customers requirements.

If it is necessary to reformat or replace your Hard Drive, Color Profiles are posted on KDAconnect for download and can be reinstalled via USB and selecting the Install Button in MM U485.

306ci/356ci/406ci Color Profile Release Notes


Driver Selectable for Print 306ci/356ci/406ci

When Printing, the Print Driver Properties will show this setting under Color Reproduction “Printer Setting” shown on the Imaging tab. You can also overwrite the Kyocera profile if custom color reproduction is required as the default. You can add an additional color profile as Color Table 2, which is available by manually clicking the Color Reproduction dropdown and selecting “Custom Table” from the Printer Driver.



356ci/406ci only

Second Profile selectable as Custom Table



306ci/356ci/406ci Color Profile Release Notes

306ci Color Profiles

Color Profiles are not preloaded on the 306ci.

A Color Profile can be added to Color Table 1 (Default) overwriting the Kyocera color reproduction (Print) or Color Table 2 (Print) and manually selected from the Driver in the same manner as the 356ci/406ci.

One Color Profile (for Print) Color Table 1 and Color Table 2 can be uploaded via USB. **Copy Profiles are not available at this time.**

The Color Profile files on your USB that you upload are specific to Color Table 1 or Color table 2. You **do not** have to register them in Maintenance Mode. **Maintenance Mode U485 is not available on the 306ci.**

Name	Size	Type	Modified
..		File folder	
CA		File folder	3/16/2016 11:0...
FJ		File folder	3/16/2016 11:0...
HE		File folder	3/16/2016 11:0...
KO		File folder	3/16/2016 11:0...
RH		File folder	3/16/2016 11:0...
ST		File folder	3/16/2016 11:0...
TO		File folder	3/16/2016 11:0...
02R4_reset.zip	7,118	WinRAR ZIP archive	2/29/2016 10:0...

After select the desired color profile, you will need to unzip the one you require and copy one or both Print Profiles to your USB Stick. **Unplug the machine**, install the USB. **Plug the machine in**. Once Finished, Update complete will display on the panel and show the profile was successfully installed. **Unplug the Machine**, remove the USB **Plug the machine in** and turn the device ON.

S2R4_G0CAC01001.zip is Color Table 1
S2R4_G1CAC01001.zip Is Color Table 2

Name	Size	Type	Modified
..		File folder	
S2R4_G0CAC01001.zip	93,970	WinRAR ZIP archive	3/4/2015 5:22 ...
S2R4_G1CAC01001.zip	93,969	WinRAR ZIP archive	3/4/2015 5:22 ...



306ci/356ci/406ci Color Profile Release Notes

The Color Table's you upload can be confirmed through Maintenance Mode U019 or the Service Status Page.

Items	Contents
Main	Main firmware
MMI	Operation firmware
Browser	Browser firmware
Engine	Engine firmware
Engine Boot	Engine boot
RFID	RFID
Dictionary	Dictionary firmware
Option Language	Optional language firmware
Color Table1(Copy)	Color table 1 firmware (copy)
Color Table2(Copy)	Color table 2 firmware (copy)
Color Table2(Prn)	Color table 1 firmware (printer)
Color Table2(Prn)	Color table 2 firmware (printer)

Service Status Page

MFP
TASKalfa 306ci

Firmware Version: 204_2020.001.150 2025.12.12

707.7000.8.01.04
17. 51 1384 000 023 827
LAS.000.001.001.100 2025.12.12

Engine Information

MMI Version: 204000.000.000
MC Address: 00:17:00:00:00:00
IP Sub Net: 0.0.0.0

Model: 306ci

50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100

101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150

151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200

201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250

251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300

301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350

351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400

401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450

451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500

501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550

551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600

601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650

651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700

701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750

751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800

801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850

851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900

901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950

951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000

306ci/356ci/406ci Color Profile Release Notes

The Color Profile uninstall procedure differs from the 356ci/406ci since **MM U485 is not available on the 306ci.**

Color Tables 1 for Print can be restored to Kyocera Color Reproduction with the reset firmware S2R4_G000E01001.

Color Tables 2 for Print can be restored to Kyocera Color Reproduction with the reset firmware S2R4_G100E01001.

Name	Size	Type	Modified
..		File folder	
CA		File folder	3/16/2016 11:0...
FJ		File folder	3/16/2016 11:0...
HE		File folder	3/16/2016 11:0...
KO		File folder	3/16/2016 11:0...
RH		File folder	3/16/2016 11:0...
ST		File folder	3/16/2016 11:0...
TO		File folder	3/16/2016 11:0...
S2R4_reset.zip	7,118	WinRAR ZIP archive	2/29/2016 10:0...

After you unzip the file above, you will get the following two folders below. Each folder contains Four files which will reset Color Table 1 (Print) and Table 2 (Print) back to the Kyocera Color Profile.

Be sure to only load the files for the Table you want to restore on the USB Stick. Follow the same procedure you preformed for the Installation of the Custom Color Profiles.

S2R4_G000E01001 is color Table 1

S2R4_G100E01001 is color table 2


Name	Size	Packed	Type	Modified	CRC32
..			Folder		
S2R4_G000E01001			Folder	3/1/2016 10:59 ...	
S2R4_G100E01001			Folder	3/1/2016 11:00 ...	

306ci/356ci/406ci Color Profile Release Notes

356ci/406ci Only

Reference for Selecting a Custom Color Profile for Copying.

Select Color/Image Quality > Original Image



When you have a Custom Color Profile Registered for Table 1 or Table 2, The Custom Button will appear.

Select Custom and select Custom 1 or Custom 2. Custom 2 will only display when a second Color Profile is registered for Copy.

